

Banshee™ Siren Amplifier System

THE NEW SOUND IN EMERGENCY RESPONSE



Features:

- Works with one set of standard size speakers – no need to install special large speakers – saving you a tremendous amount of time on installation and space where speakers are mounted.
- Eight Universal Dual Tones (Wail, Yelp, Hyper-Yelp 1, Hyper-Yelp 2, Hi-Lo 1, Hi-Lo 2, Hyper-Lo 1, Hyper-Lo 2).
- Three Low Frequency Tones (Synchronized 1/2 Frequency, Low Frequency Yelp and Low Frequency Wail).
- Eight Low Frequency Time Out settings (7.5, 15, 22.5, 30, 37.5, 45, 52.5 and 60 seconds).
- Eight individual tones for each of the Code 3 Z3 siren tone push-button (Wail, Yelp, Hyper-Yelp 1, Hyper-Yelp 2, Hi-Lo 1, Hi-Lo 2, Hyper-Lo 1, Hyper-Lo 2).
- Operate the electronic Airhorn independently of the primary siren (by itself as an alert) or while the primary siren is in full operation.
- Unique CommandAlert and Yelp Stop tones.
- Additional tones are available when the Banshee operates with a Code 3 Z3 siren.
- Universal Dual Tone operation with most industry standard sirens.
- All inputs can be configured for positive or negative activation.
- Comes with Banshee amplifier box, the power control harness bag, and a CAT5 cable
- Banshee is very economically priced and comes with a full 5 year warranty.
- Box dimensions: 8 ½" L x 2.8" H x 5.7" W (215.9mm x 71.12mm x 144.78mm)
- 10-16 VDC
- 100W: 8 Amps @ 13.6V with 11-ohm load (100 Watt Speaker)
- 200W: 14 Amps @ 13.6V with 5.5-ohm load (2-100 Watt Speakers)
- Box weight: 3.2 pounds
- SAE J1849, CA Title 13 when properly configured

Model	Description	LIST
3450	Dual Tone & Low Frequency Siren Amp System, 100w/200w Output .	\$415.43

*All C3100 speakers purchased after 4/21/2014 will be compatible with Banshee Low Frequency tone selection.

BANSHEE

