



www.GESecurity.com

Wiring Information

Use a two-conductor, 22-gauge or larger stranded wire to connect the siren to panel terminals.

Refer to the specific control panel *installation instructions* for complete details on siren connections.

When handling the stranded wire, the red wire is positive and the black wire is negative.



Specifications

- Model No:** 13-950
- Input Voltage (red):** 5-14 V DC
- Current Consumption (red):** 150 mA maximum @ 12 V DC
- Sound Output (@ 6 V DC):** 85 dB @ 10 feet
- Operating Frequency:** 2.6-2.7 KHz
- Operating Mode:** Steady only
- Dimensions:** 4.85 x 3.92 x 3.56in (123.2 x 99.6 x 90.5 mm)
- Color:** White

