

Alarm.com WiFi Chime

ADC-W114C DATA SHEET

Key Features

- Compact wireless doorbell chime
- Antenna-free design
- Adjustable chime volume
- Customizable tones
- Configurable chime rule schedules
- Simple, plug-in installation
- Remote management and troubleshooting
- Audio alerts for video analytics and alarm events
- Secondary siren functionality



Overview

Designed to be an affordable audio accessory that works seamlessly with the Alarm.com platform, the new ADC-W114C is a customizable wireless doorbell chime with a compact and antenna-free design. Your customers can configure custom chime tones and rules, adjust chime volume, and configure audio alerts for video events. Add the Alarm.com WiFi Chime to an account to replace a mechanical chime or boost audio range in camera installations. Simply plug the ADC-W114C into a wall outlet, pair with the existing router, and configure chime rules, and enjoy enhanced audible awareness at a price you'll love.

Specifications

Wi-Fi Connection:
802.11 b/g/n/ax, 2.4 GHz

Wi-Fi Security:
WPA, WPA2, WPA3

Bluetooth Version:
Bluetooth LE 5.4

LED Indicators:
1 Multicolor LED


Buttons:
1 Multi-state Button

Chime:
2 W speaker, 105 dB

Operating Temperature:
32°F to 104°F (0°C to 40°C)

Operating Humidity:
<95% (non-condensing) RH

Dimensions (H x W x D):
2.4 x 2.4 x 2.4" (6.15 x 6.15 x 6.1cm)



Requirements

Network:
2.4 GHz connection to broadband Internet via router

Power:
100 - 240 V~, 50 - 60 Hz, 0.4 A

In the box

- ADC-W114C Alarm.com WiFi Chime
- Quick Start Guide
- Slide-On Plug Adapter (US Blade Included)

Status light guide

Off:
Power off

Blinking yellow:
Power cycle

Solid red:
No local or Internet connection

Blinking red:
Device powered on, booting up

Alternating red and green:
Factory Reset

Solid green:
Connected to Alarm.com

Blinking blue:
WPS mode

Blinking white:
Wi-Fi Access Point mode

Alternating blue and green:
Firmware Update

Blinking green:
Local connection, no Internet connection