

# LED Bulb technical specifications.

Modified on: Thu, 9 Mar, 2017 at 11:05 PM

This page lists the technical specifications for **LED Bulb** (<http://aeotec.com/z-wave-led-lightbulb>) and form part of the larger **LED Bulb** (<https://aeotec.freshdesk.com/solution/articles/6000056917-led-bulb-user-guide->) **user guide**.  
(<https://aeotec.freshdesk.com/solution/articles/6000056917-led-bulb-user-guide->)

**Name:** LED Bulb

**Model number:** ZW098.

**Repeater:** Yes

**Beaming:** Yes

**AES128 Security:** Yes

**Z-Wave Plus Certified:** Yes

**Bulb holder type:**

E26 for USA version,

E27 for EU/AU version.

**Max operating power:** 9W.

**Max brightness:** 850 lumens.

**Rated color temperature:** 4700K.

**Life Use:** 50000 hours.

**Operating temperature:** 0 C to 40 C /32 F to 104 F. Relative humidity: 8% to 80%.

**Operating distance:** Up to 492 feet/150 meters outdoors.

## AC Input:

Version	Input (Standby Power)	Working band
AU	230V 50Hz, Max: 0.7W	921.42MHz
BR	220V 60Hz, Max: 0.7W	921.42MHz
CN	220V 50Hz, Max: 0.7W	868.40MHz
EU	230V 50Hz, Max: 0.7W	868.42MHz
IL	230V 50Hz, Max: 0.7W	916.02MHz
IN	230V 50Hz, Max: 0.7W	865.20MHz
UK	230V 50Hz, Max: 0.7W	868.42MHz
US	120V 60Hz, Max: 0.5W	908.42MHz

## Supported Commands.

	Non-Secure	Secure
--	------------	--------

Node Info Frame	COMMAND_CLASS_ZWAVEPLUS_INFO V2 COMMAND_CLASS_SWITCH_MULTILEVEL V2 COMMAND_CLASS_SWITCH_COLOR V1 COMMAND_CLASS_SWITCH_ALL V1 COMMAND_CLASS_SCENE_ACTUATOR_CONF V1 COMMAND_CLASS_SCENE_ACTIVATION V1 COMMAND_CLASS_CONFIGURATION V1 COMMAND_CLASS_ASSOCIATION_GRP_INFO V1 COMMAND_CLASS_ASSOCIATION V2 COMMAND_CLASS_MANUFACTURER_SPECIFIC V2 COMMAND_CLASS_VERSION V2 COMMAND_CLASS_FIRMWARE_UPDATE_MD V2 COMMAND_CLASS_POWERLEVEL V1 COMMAND_CLASS_SECURITY V1 COMMAND_CLASS_DEVICE_RESET_LOCALLY V1 COMMAND_CLASS_MARK V1 COMMAND_CLASS_HAIL V1	COMMAND_CLASS_ZWAVEPLUS_INFO V2 COMMAND_CLASS_VERSION V2 COMMAND_CLASS_MANUFACTURER_SPECIFIC V2 COMMAND_CLASS_SECURITY V1 COMMAND_CLASS_DEVICE_RESET_LOCALLY V1 COMMAND_CLASS_MARK V1 COMMAND_CLASS_HAIL V1
Security Command Supported Report Frame		COMMAND_CLASS_SWITCH_MULTILEVEL V2 COMMAND_CLASS_SWITCH_COLOR V1 COMMAND_CLASS_SWITCH_ALL V1 COMMAND_CLASS_SCENE_ACTUATOR_CONF V1 COMMAND_CLASS_SCENE_ACTIVATION V1 COMMAND_CLASS_CONFIGURATION V1 COMMAND_CLASS_ASSOCIATION_GRP_INFO V1 COMMAND_CLASS_ASSOCIATION V2 COMMAND_CLASS_MANUFACTURER_SPECIFIC V2 COMMAND_CLASS_VERSION V2 COMMAND_CLASS_FIRMWARE_UPDATE_MD V2 COMMAND_CLASS_POWERLEVEL V1 COMMAND_CLASS_DEVICE_RESET_LOCALLY V1 COMMAND_CLASS_HAIL V1

