



Wire the ADC-VDB770 to two chimes

The ADC-VDB770 can support up to two digital or mechanical chimes simultaneously by using two power modules. The chimes themselves must be wired in parallel rather than in a series.

For more information about enrolling the ADC-VDB770, see [Alarm.com Video Doorbell \(ADC-VDB770\) - Installation Guide](#).

Wire the ADC-VDB770 to two chimes

Wiring

1. On the first power module, attach the white wires interchangeably to the *FRONT* and *TRANS* terminals on the chime.
2. On the second power module, attach the white wires interchangeably to the *REAR* and *TRANS* terminals on the chime.
3. Attach one of each of the power modules to the transformer using a wire connector.
4. Attach one of each of the power modules to the ADC-VDB770 using a wire connector.
5. On the ADC-VDB770, attach the remaining wire to the transformer.

Diagram

