

CD-** Cable Pinout for the APG Model 320 Interface Cash Drawer

<u>Cash Drawer Internal Wiring</u>			-- STATUS SWITCH --				----- SOLENOID -----			
			GND	COM	NO	NC	R SOL (-24V)	F SOL (+24V)	R SOL (-12V)	F SOL (+12V)
320 Interface	8P8C Modular Jack	Pinouts:	1	2	3	4	6	7		
420 Interface	8P8C Modular Jack		1	2	3	4			5	8
520 Interface	8P8C Modular Jack		1	2	3	4	6	7	5	8

<u>Cable PN</u>	<u>Host End Connector</u>	<u>Length (in)</u>	GND	COM	NO	NC	R SOL (-24V)	F SOL (+24V)	R SOL (-12V)	F SOL (+12V)
CD-001A	6P6C Mod Plug	60	1	6		3	2	4		
CD-001B	6P6C Mod Plug	60	1	6		3	5	4		
CD-002A	MOLEX 4PIN	60					2	1		
CD-003A	6P6C Mod Plug	60		5	4		2	3		
CD-003B	6P6C Mod Plug	60		5	4		1	3		
CD-005A	6P6C Mod Plug	60	1	6	3		2	4		
CD-005A10	6P6C Mod Plug	120	1	6	3		2	4		
CD-005B	6P6C Mod Plug	60	1	6	3		5	4		
CD-009A	6P6C Mod Plug	60		2		3	5	4		
CD-009A10	6P6C Mod Plug	125		2		3	5	4		
CD-009B	6P6C Mod Plug	60		2		3	1	4		
CD-010	BNC	60					SHELL	CENTER		
CD-013A	6P6C Mod Plug	60	1				2	3		
CD-013B	6P6C Mod Plug	60	1				5	3		
CD-014A	6P6C Mod Plug	60	1	6	4		2	3		
CD-014B	6P6C Mod Plug	60	1	6	4		5	3		
CD-017A	6P6C Mod Plug	60	1	6	4 [4.7K Res.]				2	3
CD-D1D2	2 - 6P6C Mod Plugs	splitter	1-1-1	6-6-6	3-3-3		2-2-2	4-4-4		
CD-D1D2EP	2 - 6P6C Mod Plugs	splitter	1-1-1	6-6-	-3-3	3- -6	2-2-2	4-4-4		

Refer to the manufacturer's pinout documentation for other connector types.

