What do the LEDs on the ADC-V716 mean?

LED reference guide

LED pattern	Description
Off	Power off
Solid green 	Connected to Alarm.com
Blinking green 	Local network connection
Blinking red 	Power on, camera booting
Solid red 	No local or Internet connection

LED pattern	Description
Blinking blue 	Wi-Fi Protected Setup (WPS) mode (press and hold button for 4-6 seconds)
Blinking white	Bluetooth Enrollment (BLE) mode and Access Point (AP) mode (press and hold button for 7-9 seconds)
Blinking red and green 	Reverting to factory default settings (press and hold button for 10-12 seconds)
Blinking red and blue 	Perimeter Guard camera light alert activation

Caution: Factory resetting the device will require it to also be deleted from the customer account and re-enrolled.